

UTILITY PATENT APPLICATION TRANSMITTAL

Assistant Commissioner for Patents
Washington, D.C. 20231
BOX PATENT APPLICATIONAttorney Docket No.: PA000469
Date: November 15, 2000
Express Mail Label No.: EL653020462US

Dear Sir:

Transmitted herewith for filing is the patent application of:

Inventor(s): Stein A. Lundby

For: Method and Apparatus for Reducing Transmission Power in a High Data Rate System.

Enclosed are:

1. ☒ Patent application (25) total pages.
2. ☒ Drawings: ☐ Formal () sheet(s) or ☒ Informal (5) sheet(s).
3. ☒ Declaration/Power of Attorney: ☐ Signed ☒ Unsigned
4. ☐ An Assignment () pages and Recordation Form Cover Sheet.
5. ☐ A Preliminary Amendment () pages.
6. ☐ Information Disclosure Statement (IDS):
 - a. ☐ PTO-1449
 - b. ☐ Copies of IDS Citations (number of citations:)
7. ☐ Other:

CLAIMS:	(a) Filed	(b) Extra Claims	Large Entity Fee	Fee Paid
Total*	41 - 20	21	x \$18 =	\$378.00
Independent**	4 - 3	1	x \$80 =	\$80.00
Multiple Dependent Claim(s): <input type="checkbox"/> No <input type="checkbox"/> Yes			\$270	\$
APPLICATION FILING FEE			\$710	\$710.00
			TOTAL FEE	\$1168.00

*If the number in column a is less than 20, enter 0 in column b.

**If the number in column b is less than 3, enter 0 in column b.

8. ☐ A check in the amount of \$_____ is enclosed to pay the filing fee.
9. ☒ Please charge Deposit Account No. 17-0026 of QUALCOMM Incorporated the amount of \$1168.00. The Commissioner is hereby authorized to charge payment of any additional fees which may be required, or credit any overpayment, to said Deposit Account No. 17-0026. A duplicate of this sheet is enclosed for fee processing.
10. ☒ The Commissioner is further hereby authorized to charge to said Deposit Account No. 17-0026, pursuant to 37 CFR 1.25(b), any fee whatsoever which may become properly due or payable, as set forth in 37 CFR 1.16 to 37 CFR 1.18 inclusive, for the entire pendency of this application without specific additional authorization.

Date: November 15, 2000

Signature: Byron YafusoByron Yafuso, Reg. No. 45,244
(858) 658-3868QUALCOMM Incorporated
Attn: Patent Department
5775 Morehouse Drive
San Diego, California 92121-1714
Telephone: (858) 651-1179
Facsimile: (858) 658-2502

PATENT

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

In Re Application of)
Stein A. Lundby) For: Method and Apparatus for
Serial No. Unknown) Reducing Transmission Power
Filed: Herewith) in a High Data Rate System
Group Art Unit: Unknown



CERTIFICATE OF MAILING UNDER 37 CFR § 1.10

Asst. Commissioner of Patents
BOX PATENT APPLICATIONS
Washington, D.C. 20231

Dear Sir:

"Express Mail" mailing label No. EL653020462US
Date of Deposit NOVEMBER 15, 2000

I hereby certify that the following papers are being deposited with the United States Postal Service "Express Mail Post Office to Addressee" service under 37 CFR § 1.10 on the date indicated above and is addressed to the Asst. Commissioner of Patents, Box Patent Applications, Washington, D.C. 20231:

PATENT APPLICATION IN 25 PAGES; TRANSMITTAL LETTER IN DUPLICATE; UNSIGNED DECLARATION/POWER OF ATTORNEY; 5 SHEETS OF INFORMAL DRAWINGS; AND POSTCARD

Kayla R. Seignious

(Name)

Kayla R. Seignious
(Signature)

QUALCOMM Incorporated
5775 Morehouse Drive
San Diego, California 92121-1714
Telephone: (858) 845-3313
Facsimile: (858) 658-2502

METHOD AND APPARATUS FOR REDUCING TRANSMISSION POWER IN A HIGH DATA RATE SYSTEM

5 The current invention relates to wireless data communication. More particularly, the present invention relates to a novel method and apparatus for gating or reducing reverse link transmissions in a communication system that supports high data rate (HDR) services.

10 The word "exemplary" is used exclusively herein to mean "serving as an example, instance, or illustration." Any embodiment described as an "exemplary embodiment" is not to be construed as necessarily preferred or advantageous over other embodiments described herein.

In the accompanying drawings:

15 **FIG. 1** is a diagram of an exemplary HDR communication system.

FIG. 2a is a graph of reverse link transmission gating or reduction using an access metric that is based on carrier-to-interference ratio.

FIG. 2b is a graph of reverse link transmission gating or reduction using an access metric that is based average throughput.

20 **FIGS. 3** is a flowchart of a method to determine when to gate or reduce reverse link transmissions.

FIG. 4 is a diagram of an access terminal apparatus.

25 OVERVIEW

The present invention is directed to a method and apparatus for periodically reducing reverse link transmissions in a high data rate (HDR) communication system. An exemplary HDR system is described in U.S. Patent
30 Application Serial No. 08/963,386 entitled "METHOD AND APPARATUS FOR HIGH RATE PACKET DATA TRANSMISSION," assigned to the assignee of the present invention, and referred to herein as the '386 application. In the '386 application, a system is described wherein a HDR subscriber station transmits data on a reverse link using a CDMA waveform of multiple orthogonal
35 channels. Each subscriber station sends a reverse link signal containing data rate control (DRC) information. Each base station transmits a forward link signal that is divided into time slots. During each time slot, each base station

transmits data to a subscriber station based on DRC information received from that subscriber station.

In an exemplary embodiment, the DRC information is a quantization of the carrier-to-interference (C/I) ratio of the received forward link signal as measured by the subscriber station. Alternatively, the subscriber station may substitute C/I information for the DRC information. The base station may transmit strictly at the data rate dictated by the DRC or C/I information received from a subscriber station, or may choose the data rate based on additional information. If the base station does not adhere to the data rate dictated by the subscriber station, then the subscriber station may decode a rate indicator signal on the forward link or perform some form of blind rate detection.

FIG. 1 is a diagram of an exemplary HDR communication system. An HDR subscriber station, referred to herein as an access terminals (AT's) **102**, may be mobile or stationary, and may each communicate with one or more HDR base stations **104**, referred to herein as modem pool transceivers (MPT's). Access terminals **102** transmit and receive data packets through one or more modem pool transceivers **104**, to an HDR base station controller (not shown), referred to herein as a modem pool controller (MPC). Modem pool transceiver's and MPC's are parts of a network called an access network. An access network transports data packets between multiple access terminals. The access network may further be connected to additional networks outside the access network, such as a corporate intranet or the Internet, and may thus transport data packets between each access terminal and such outside networks. An access terminal that has established an active traffic channel connection with one or more modem pool transceiver's is called an active access terminal, and is said to be in a traffic state. An access terminal may be any data device that communicates through a wireless channel or through a wired channel, for example using fiber optic or coaxial cables. An access terminal may further be any of a number of types of devices including, but not limited to PC card, compact flash, external or internal modem, or wireless or wireline phone. The communication link through which an access terminal **102** sends signals to a modem pool transceiver **104** is called a reverse link. The communication link through which modem pool transceiver **104** sends signals to access terminal **102** is called a forward link. Reverse link signals transmitted by one access terminal, for example **102a**, interfere with reverse link signals transmitted by other access terminals, for example **102b** and **102c**. This interference limits the reverse link capacity of the HDR system. Gating, as used herein, refers to

turning off transmission, or transmitting at approximately zero power, of a signal or signal component.

In order to reduce the interference caused by reverse link transmissions, the access terminal periodically gates or reduces its reverse link transmissions.

5 The periods of gating or reduction are designed such that they occur during periods when forward link and reverse link throughput will not be degraded. For example, an access terminal estimates parameters used by the access network to select an access terminal as a destination of forward link transmissions. An example of such an access network selection algorithm is
10 described in detail in U.S. Patent Application Number 09/317,298 entitled "TRANSMITTER DIRECTED, MULTIPLE RECEIVER SYSTEM USING PATH DIVERSITY TO EQUITABLY MAXIMIZE THROUGHPUT," assigned to the assignee of the present invention, referred to herein as the '298 application. The '298 application includes a description of an algorithm that allocates forward
15 link resources such that the throughput of the system is maximized while ensuring that each user is granted equitable access to the communication system.

The selection algorithm used by the access network generally selects an access terminal based on throughput of data transmitted to, and DRC signals
20 received from, all active access terminals. Using the same or a similar selection algorithm, the access terminal calculates an access metric and an access metric threshold in order to predict when the modem pool transceiver is unlikely to select the access terminal to receive forward link data. Rather than transmit a DRC rate that will not result in the access terminal being selected, the access
25 terminal sends a partial reverse link signal with the DRC signal omitted, or perhaps sends no reverse link signal at all. In order to avoid a dropped call, the access terminal limits the time during which it reduces its transmission of reverse link signals to a predetermined maximum transmitter shut-off period. If, after reducing its reverse link transmission, the access terminal's access
30 metric subsequently rises above the access metric threshold, or after the maximum transmitter shut-off period, the access terminal resumes transmitting full reverse link signal.

DETAILED DESCRIPTION

35

FIG. 2a shows an exemplary pattern of reverse link transmission gating or reduction **210** occurring when the access terminal uses an algorithm based on forward link carrier-to-interference (C/I) values **202**. The exemplary forward link carrier-to-interference (C/I) curve **202** is shown as a function of time in a

typical Rayleigh fading environment. As the access terminal moves within the different areas of modem pool transceiver coverage, fading causes the C/I of the forward link signal received by the access terminal to exhibit round peaks 214 and sharp valleys 216.

5 In an exemplary embodiment, the access terminal performs low-pass filtering or windowing of the C/I in order to produce an averaged C/I value. For example, the access terminal could create an averaged C/I value by calculating an unweighted average of the C/I values over a predetermined number of prior time slots. Alternatively, the access terminal could generate
10 the averaged C/I value by performing a weighted average of previous C/I values. This averaged C/I value could be used to compute a changing C/I threshold 204 that is compared with the C/I of the current time slot 202, or "current C/I." The C/I value and C/I threshold may be viewed as an "access metric" and an "access metric threshold," respectively, and are used by the
15 access terminal to predict when the access terminal is likely not to be selected to receive forward link data.

At the points 206 where the C/I value drops to a value less than the C/I threshold, then the access terminal stops transmitting a reverse link signal. At the points 208 where the C/I value subsequently rises to a value greater than
20 the C/I threshold, the access terminal begins transmitting a reverse link signal again, including DRC information. In the exemplary figure, the gating pattern 210 shows the gating pattern for reverse link transmission of the access terminal in relation to C/I curve 202 and C/I threshold 204. The gating pattern 210 is high when the access terminal is transmitting a full reverse link signal, and low
25 when the access terminal gates or reduces reverse link transmissions.

The algorithm used to compute the C/I threshold from the averaged C/I value may be constant or may vary over time. For example, the C/I threshold could be simply computed by multiplying the averaged C/I value by a constant k where $k < 1$. In an alternate embodiment, k varies based on the length of time
30 212 during which the access terminal has stopped transmitting, called a transmitter shut-off period. As the transmitter shut-off period becomes longer, k increases. In an exemplary embodiment, k becomes zero after a predetermined maximum transmitter shut-off period, for example two seconds. Among other benefits, this mitigates undesirable side-effects of shutting off
35 reverse link transmissions, such as termination of the connection by the modem pool transceiver or decreased effectiveness of reverse link power control mechanisms. In an exemplary embodiment, the access terminal ignores reverse link power control commands received in association with time slots falling within the transmitter shut-off period.

In an alternate embodiment, instead of comparing a C/I threshold to a C/I value for a slot, the access terminal compares a DRC rate to a computed selection estimate A . Based on the algorithm used by the access network to select destination access terminals for forward link transmissions, the access terminal uses its own algorithm to compute the selection estimate A . In an exemplary embodiment, the selection estimate is computed based on an average forward link throughput associated with the access terminal. For example, the access terminal may compute the average number of data bytes per second received during the previous 50 forward link time slots (filtered using a finite impulse response, or FIR, filter). Alternatively, the average throughput may be computed using an infinite impulse response, or IIR, filter. This average may be based on the data rate requested by the access terminal. Alternatively, if the protocol used by the access terminal and the access network provides for acknowledgments of forward link data, the access terminal may compute an average throughput based on a data rate granted. With each forward link time slot that passes without the access terminal receiving data, this selection estimate decays.

The selection algorithm used by the access network may be designed to balance the desire to maximize forward link throughput against preventing any access terminal from being starved for forward link data. The access network often uses a selection algorithm based on information maintained for each active access terminal, for example historical forward link throughput and the presence of data in the access terminal's forward link data queue. An access terminal is only eligible for selection if there is data in its forward link data queue. The access network may also use DRC rate information received from the access terminal in selecting a destination access terminal.

In an exemplary embodiment, a modem pool transceiver transmits forward link data to an access terminal during any particular time slot. The modem pool transceiver may alternatively transmit forward link data to more than one access terminal during a time slot. An access terminal is only eligible for selection if there is forward link data that needs to be sent to the access terminal. The access network maintains a forward link data queue for each active access terminal. When there is no forward link data left to send to an access terminal, the forward link data queue associated with that access terminal eventually becomes empty. In an exemplary embodiment, the selection of a destination access terminal is based both on an access metric that the access network maintains for each access terminal and on the condition of the access terminal's forward link data queue. For each modem pool transceiver, an access terminal having a large access metric value (or in many

cases, the largest access metric value) is selected from among the access terminals having non-empty forward link data queues to receive forward link transmissions.

Over time, if the number of active access terminals, channel conditions, and data rates remain constant, a steady state network threshold value of access metric value emerges. Any access terminal having an access metric value greater than the network threshold is immediately selected to receive forward link data. Any access terminal having an access metric value less than the network threshold is not selected to receive forward link data.

FIG. 2b shows a pattern of reverse link transmission gating using an alternative algorithm. In an exemplary embodiment, reverse link transmission gating or reduction is based on an access metric AM computed as a function of average throughput and measured forward link channel conditions, such as DRC values. The access terminal maintains a dynamically changing access metric threshold Th_{AM} . For each slot, the access terminal computes the current value of access metric AM and compares it with the access metric threshold Th_{AM} . Based on the comparison, the access terminal determines whether to gate or reduce the reverse link signal transmitted during the next reverse link time slot. Alternatively, the access terminal may gate or reduce a select subset of components of the reverse link signal based on the comparison, for example the DRC signal component.

In an exemplary embodiment, the access terminal reduces or gates its reverse link transmissions whenever AM is less than Th_{AM} . In an alternate embodiment, the access terminal reduces or gates its reverse link transmissions whenever AM is less than $S \cdot Th_{AM}$, where S is a scaling factor less than 1. The scaling factor S may be constant or may vary with time. In an exemplary embodiment, S diminishes such that it equals zero after a predetermined maximum transmitter shut-off period, for example two seconds.

In an exemplary embodiment, the access terminal computes the access metric AM based on the equation:

$$AM = ChC / T_{AVG} \quad \text{Eq. 1}$$

where:

ChC is a measured instantaneous channel condition, for example the DRC value,

T_{AVG} is the average throughput value calculated according to Eq. 2, and AM is the access metric value for the current time slot.

In an exemplary embodiment, the average throughput T_{AVG} for a time slot is calculated according to the equation:

$$T_{AVG} (new) = [(1 - k) \times T_{AVG} (previous)] + [(k) \times T_{CUR}] \quad \text{Eq. 2}$$

where:

k is a filter constant,

$T_{AVG}(new)$ is the new value of average throughput,

$T_{AVG}(previous)$ is the previous value of the average throughput, for
 5 example the average throughput calculated during the previous time slot, and

T_{CUR} is the current value of the data throughput, for example either zero
 when the access terminal receives no data, or the data rate when the access
 terminal is receiving data. As discussed above, this through may be either the
 throughput requested by the access terminal or the throughput granted by the
 10 access network.

In an exemplary embodiment as shown in **FIG. 2b**, the DRC value is
 used to represent instantaneous channel condition ChC when computing access
 metric AM 250. In an exemplary embodiment, the DRC value is a data rate
 15 chosen from a set of available data rates based on carrier to interference ratio
 (C/I) measured at the access terminal. Each DRC value is valid over a range of
 C/I values, and is therefore a quantization of C/I . As shown in Eq. 1, the
 average throughput is computed in an exemplary embodiment by dividing the
 channel condition ChC by the average throughput T_{AVG} . Though C/I is
 20 continuous over time, when C/I crosses a threshold from one DRC rate range
 into another, the DRC value changes in steps. Consequently, the access metric
 AM exhibits step changes 260 in value when the DRC value changes.

The average throughput of an access terminal decreases while the access
 terminal does not receive forward link transmissions, and increases during time
 25 slots when the access terminal receives data. Consequently, the access metric
 AM increases during periods 254 while the access terminal is not receiving
 forward link data, and decreases during periods 252 while the access terminal is
 receiving forward link data.

In an exemplary embodiment, the access network selects one destination
 30 access terminal per forward link time slot to receive data. An access terminal is
 only eligible for selection if there is data in its forward link data queue. From
 among the eligible access terminals, an access terminal is selected that has the
 greatest access metric value. The access metric value of the access terminal
 selected by the access network may vary based on additional factors such as the
 35 number of active access terminals and received DRC signals. If network
 conditions remain relatively constant (i.e. the number of active access terminals
 remains constant, forward link channel conditions are stable, and all access
 terminals receive data such that their forward link data queues are never
 empty), the access metric of the access terminal selected for each slot will

stabilize to a relatively constant value. An access terminal having an access metric that is less than this stabilized value will not be selected. This stabilized value may be viewed as a network threshold that can be used to predict whether an access terminal having a particular access metric will be selected.

5 Even when various factors that affect the network threshold are not stable over time, an access terminal can estimate the network threshold. As described above, an access terminal will only be selected to receive forward link data if its access metric value is greater than this access network threshold. In an exemplary embodiment, the access terminal maintains an access metric
10 threshold and uses it to predict whether it might be selected by the access network. In an exemplary embodiment, the access metric threshold is an estimate of the network threshold.

The actual network threshold is a function of the number of active access terminals, the presence of data in each access terminal's forward link data
15 queue, and other changing parameters that are generally unavailable to individual access terminals. The access terminal can only accurately predict whether it will be selected if it has access to the same parameters and uses the same algorithm as the access network. Thus, the access terminal cannot generally predict whether it will be selected with complete accuracy.

20 Even using an imperfect estimate, an access terminal may increase the reverse link capacity of the network by selectively gating or reducing its reverse link signals. In an exemplary embodiment, the access network provides an access terminal with some of this information to more accurately determine whether it is likely to be selected by the access network. For example, in an
25 exemplary embodiment, the access network periodically transmits on the forward link the number of active access terminals.

Though the accuracy of an access terminal's predictions are best when both access terminal and access network use identical algorithms, one skilled in the art will recognize that the algorithms need not be identical to achieve
30 improved reverse link capacity. In an exemplary embodiment, the access terminal uses an estimate of the network threshold as its access metric threshold. In other embodiments, the access terminal uses an access metric threshold that is not an estimate of the network threshold. Either way, the access terminal limits its transmit power when the access metric is less than the
35 access metric threshold.

The access terminal compares its access metric value to the access metric threshold in order to predict whether it might be selected to receive forward link data. An access metric value that is less than the access metric threshold indicates that the access terminal is unlikely to be selected to receive forward

link data at that time, or during the next forward link time slot. If the access terminal determines that it is unlikely to be selected and has no reverse link data to transmit, then the access terminal minimizes its contribution to reverse link interference by reducing the power of its reverse link signal. In an exemplary embodiment, the access terminal reduces reverse link transmission power by transmitting only a subset of reverse link signal components, for example only a reverse link pilot. In an alternate embodiment, the access terminal may elect to refrain from sending a reverse link signal entirely for a period of time.

The exemplary graph in FIG. 2b shows access metric *AM* in graph line 250, access metric threshold in dotted graph line 270, and transmitter state in graph line 272 in accordance with an exemplary embodiment. The transmitter state 272 is high while the access terminal is transmitting a reverse link signal and low during periods while the access terminal gates or reduces its reverse link signal. Additionally in FIG. 2b, graph line 274 shows whether the access terminal has been selected and is receiving forward link data from the access network. When graph line 274 is high, the access terminal is receiving forward link data. When graph line 274 is low, the access terminal is not receiving forward link data.

In FIG. 2b, the access metric threshold 272 begins at a value 258a that is less than that of access metric 250. While the access terminal is receiving forward link data, its access metric steadily decreases 252a. At time T_1 , the channel conditions degrade such that the DRC value is decreased. The channel conditions could degrade for any of a number of reasons including Rayleigh fading caused by multipath interference, an object appearing in the direct path between the access terminal and the modem pool transceiver, or increased distance between the access terminal and the transmitting modem pool transceiver. The decrease in DRC causes the access metric to drop below the access metric threshold 258a at time T_1 . Consequently, at time T_1 , the access terminal stops transmitting as shown in the graph of transmitter state 272. During this period, the access terminal does not transmit a DRC signal, and therefore receives no forward link data.

While the access terminal is not receiving data, the access metric gradually increases as shown. At time T_2 , the DRC value changes to a greater value, and the access metric increases 260b. At time T_2 , the access metric takes on a value greater than the access metric threshold. Based on the comparison between the access metric and the access metric threshold, the access terminal resumes transmitting a reverse link signal. In the example, although the access metric is greater than the access metric threshold, the access terminal does not

receive forward link data. This could mean either that the network has no forward link data to send the access terminal or that the actual network threshold is greater than the access metric threshold. While the access terminal is not receiving data, the access metric steadily increases **254b**.

5 At time T_3 , the DRC value increases again, causing another step increase **260c** in the access metric. At the new access metric value, the access network immediately begins sending forward link traffic to the access terminal. In the example, the access terminal then adjusts its access metric threshold to equal the greatest access metric value **258b** reached during the period **254b** immediately
10 preceding the jump in DRC value at time T_3 . In an alternate embodiment, the access terminal adjusts its access metric threshold to the same greatest access metric value **258b**, less a predetermined guard value, for example 3dB.

While the access terminal is receiving forward link data, the access metric value steadily decreases **252b**. At time T_4 the access terminal stops
15 receiving forward link data, either because another access terminal is being served by the modem pool transceiver or because there is no more forward link to send. While the access terminal is not receiving forward link data, the access metric steadily increases **254c**.

At time T_5 , the DRC value drops significantly, causing a step decrease
20 **260d** in the access metric. The new access metric value is less than the access metric threshold, so the access terminal stops transmitting a reverse link signal. During this period, the access terminal does not transmit a DRC signal, and therefore receives no forward link data. While the access terminal does not receive forward link data, the access metric steadily increases **254d**.

25 As discussed above, it is undesirable to the access terminal to shut off its transmitter for too long. In the example, the access terminal turns its transmitter back on after a maximum transmitter shut-off period even if the access metric is still less than the access metric threshold. In the example, the maximum transmitter shut-off period ends at time T_6 . At that time, the access
30 terminal resumes transmitting a reverse link signal, even if the access metric is still less than the access metric threshold

At time T_7 , the DRC value increases again, causing another step increase
35 **260d** in the access metric. At the new access metric value, the access terminal immediately begins receiving forward link traffic from the access network. In the example, the access terminal then adjusts its access metric threshold to equal the greatest access metric value **258c** reached during the period **254d** immediately preceding the jump in DRC value at time T_7 . In an alternate embodiment, the access terminal adjusts its access metric threshold to the same

greatest access metric value 258c, less a predetermined guard value, for example 3dB.

While the access terminal is receiving forward link data, the access metric value steadily decreases 252c. At time T_8 the access terminal stops
5 receiving forward link data, either because another access terminal is being served by the modem pool transceiver or because there is no more forward link to send. While the access terminal is not receiving forward link data, the access metric calculated in the access terminal steadily increases 254e.

At time T_9 , the access network begins sending forward link data to the
10 access terminal again. Because the beginning of transmission does not coincide with a sudden increase in the access metric, the access terminal assumes that the network threshold is less than or equal to the current access metric value. The access terminal sets its access metric threshold to a value that is less than the current access metric value by a predetermined guard value, for example 3dB.
15 While the access terminal is receiving forward link data, the access metric value steadily decreases 252d. At the same time, the access metric threshold decreases 258d such that it remains less than the access metric value by the guard value.

As mentioned above, refraining from sending any reverse link signal for
20 a prolonged period is generally undesirable. One reason is that it interferes with reverse link power control algorithms. Another is that if the access network receives no reverse link signal from an access terminal, it may assume that its communication link with the access terminal has been lost. Consequently, the access network will terminate its connection with the access
25 terminal.

In an exemplary embodiment, while an access terminal is transmitting no reverse link signal, the access terminal ignores associated reverse link power control commands from the access network. In an alternate embodiment, the modem pool transceiver algorithms ignore frame errors on the reverse link if
30 the modem pool transceiver determines that the access terminal has gated or reduced its reverse link transmissions. This prevents the power control algorithm at the modem pool transceiver from erroneously increasing its outer-loop set point.

In an exemplary embodiment, the access terminal refrains from sending
35 any reverse link signal during a period in which its access metric is less than the access metric threshold. If, however, this period lasts longer than a predetermined maximum transmitter shut-off period, the access terminal turns its transmitter back on again. The access terminal continues transmitting a reverse link signal for at least a predetermined minimum transmitter

restoration period, for example 5 milliseconds. The minimum transmitter restoration period is designed to ensure that the access network will not terminate its connection with the access terminal because of the transmitter shut-off, and to allow the modem pool transceiver searcher to accurately track reverse link multipath components.

In an exemplary embodiment where an access terminal refrains from sending any reverse link signal for a period, it may also be advantageous after such a period to resume transmitting some signals before resuming transmitting others. For example, an access terminal may resume transmitting a pilot signal before resuming transmission of other reverse link signal components. This practice enables pre-loading of pilot filters and multipath tracking within the modem pool transceiver.

In any of the embodiments described above, the access terminal may determine its access metric threshold based on parameters that apply to one or more other access terminals. In an exemplary embodiment, such parameters are periodically received from the access network. These parameters may include, but are not limited to, the number of active users being serviced by a modem pool transceiver or by the access network, or the access metric or average throughput value of the previously selected access terminal. One skilled in the art will appreciate that the particular additional parameters received from the access network may be different than the parameters described above without departing from the methods described herein.

One skilled in the art will recognize that the values discussed above, such as maximum transmitter shut-off period and minimum transmitter restoration period, are used only as examples and may be changed without departing from the described embodiments. In addition, reducing various other combinations of reverse link signal components than those specifically described should be viewed as within the scope of the described embodiments.

FIG. 3 is a flowchart showing an access terminal method for determining when to reduce or entirely shut off reverse link transmissions. For each forward link time slot, the access terminal measures the forward link channel conditions at step **302**. The parameters measured and used to determine forward link channel conditions include such parameters as carrier-to-interference (C/I) of the received signal and received signal power. From the channel condition measurements, the access terminal determines, at step **304**, an access metric *AM* value. In an exemplary embodiment, *AM* is calculated using a data rate control (DRC) value and an average throughput value as described above.

At step 306, the access terminal compares the new AM value to an access metric threshold TH_{AM} to determine whether to transmit a full reverse link signal. If AM is greater than TH_{AM} , then at step 310 the access terminal transmits a full reverse link signal. In an exemplary embodiment, a full reverse link signal includes pilot and DRC information. If AM is less than TH_{AM} , then the access terminal checks, at step 307, whether its reverse link transmissions had already been reduced in the previous reverse link time slot. If reverse link transmissions were already being reduced, the access terminal determines for how long they have been reduced. The duration of the reduction is compared to a maximum transmitter shut-off period. If the duration of the reduction is greater than the maximum transmitter shut-off period, then the access terminal resumes transmitting a full reverse link signal at step 310.

In an exemplary embodiment, the access terminal also limits the length of time that it transmits a full reverse link signal while AM is less than TH_{AM} . At step 307, the access terminal checks timers to determine whether to reduce reverse link signal transmissions at step 308 or to transmit a full reverse link signal at step 310. For example, during a long period during which AM remains less than TH_{AM} , an access terminal reduces its reverse link transmissions for the maximum transmitter shut-off period. After that, if AM is still less than TH_{AM} for a minimum transmitter restoration period, the access terminal again reduces its reverse link transmissions. This cycle of restoring full reverse link signal transmissions after a maximum transmitter shut-off period and reducing reverse link signal transmissions after a minimum transmitter restoration period continues until AM becomes greater than TH_{AM} .

As described above, at step 308 the access terminal may reduce its reverse link transmissions in different ways. In an exemplary embodiment, the access terminal gates, or stops transmitting, all components of the full reverse link signal. In another embodiment, the access terminal transmits a reverse link signal that is complete except for lack of the DRC component. In other embodiments, the access terminal transmits some other subset of reverse link signal components. Alternatively, the access terminal may transmit some or all of the reverse link signal components at a reduced power level, but not gate them entirely.

In an exemplary embodiment, the access terminal stops transmitting all components of the reverse link signal, but resumes transmitting the pilot signal before resuming other channels. This allows pre-loading of pilot filters at the modem pool transceiver.

After either transmitting a full reverse link signal at step 310 or transmitting a reduced reverse link signal at step 308, the access terminal

processes any received forward link data at step 312 and updates T_{AVG} and TH_{AM} at step 314. Then, the access terminal begins the processing of the next time slot again by measuring forward link channel conditions at step 302.

Whether or not the access terminal transmits a full reverse link signal, the access network may continuously send reverse link power control commands to the access terminal. If the access network bases reverse link power control commands on signal components that were gated or sent at reduced power, those power control commands will not accurately reflect the reverse link channel conditions. In an exemplary embodiment, the access terminal ignores or performs special processing on any reverse link power control commands associated with periods during which the access terminal was not transmitting a full reverse link signal.

FIG. 4 shows an exemplary access terminal apparatus. In an exemplary embodiment as shown, apparatus, pilot, supplemental data, data rate control (DRC), and fundamental data signals are spread with a Walsh code, gain-controlled, and added together before being spread in complex pseudonoise (PN) spreader 410. The pilot signal is multiplied by a pilot Walsh code W_p in Walsh spreader 401a and gain-controlled in gain block 402a. The supplemental data signal is multiplied by a supplemental data Walsh code W_s in Walsh spreader 401b and gain-controlled in gain block 402b. The DRC signal is multiplied by a DRC Walsh code W_d in Walsh spreader 401c and gain-controlled in gain block 402c. The fundamental data signal is multiplied by a fundamental data Walsh code W_f in Walsh spreader 401d and gain-controlled in data gain block 402d.

In an exemplary embodiment, Walsh spreaders 401 are implemented as multipliers that multiply the different Walsh codes by the pilot, DRC, and supplemental and fundamental data signals. Prior to Walsh spreading, the pilot, DRC, and supplemental and fundamental data signals are converted into signal point mapped values, for example +1 and -1. In an alternate embodiment, signal point mapping occurs immediately prior to gain-controlling in gain blocks 402. In such an alternate embodiment, Walsh spreaders 401 perform an XOR function with the Walsh covers instead of multiplying. In an alternate embodiment, the pilot signal is spread using a "Walsh function zero" or W_0 , which is actually no spreading at all. In such an alternate embodiment, Walsh spreader 401a may be omitted.

The gain-controlled signals produced by gain blocks 402a and 402b are added together to form the output of summer 408a. The gain-controlled signals produced by gain blocks 402c and 402d are added together to form the output of summer 408b. The output of summer 408a provides the in-phase (I') or

“real” component of the signal multiplied by the complex PN code in PN spreader 410. The output of summer 408b provides the quadrature-phase (Q’) or “imaginary” component of the signal multiplied by the complex PN code in PN spreader 410. The output of complex PN spreader 410 is a complex signal having I and Q components. Each of these components is filtered using a baseband filter 412a and 412b before being upconverted in mixers 414a and 414b. The upconversion in mixers 414a and 414b is accomplished by multiplying the outputs of baseband filters 412a and 412b by sine and cosine signals as shown. The outputs of mixers 414 are then added in summer 416 to form the upconverted reverse link signal to be amplified in amplifier 418 and transmitted through antenna 420.

The gain levels applied to the various signals by gain blocks 402 are controlled by control processor 424. Control processor 424 receives timing information such as slot timing from system time processor 426. Control processor 414 then determines when to gate or reduce reverse link transmissions according to one of the algorithms or embodiments described above. Control processor 426 then compares the access metric with an access metric threshold and gates or reduces the transmit power of reverse link signals based on the comparison. In an exemplary embodiment, control processor 424 uses parameters received from the access network that apply to one or more other access terminals to determine the access metric threshold.

In general, control processor 424 gates or reduces reverse link transmissions during periods in which the access metric is less than the access metric threshold. In an exemplary embodiment, control processor 424 uses timing information from system processor 426 to regulate the duration of the period during which reverse link transmissions are gated or reduced. For example, if this period lasts longer than a predetermined maximum transmitter shut-off period, the control processor 424 causes the access terminal to resume transmitting a full reverse link signal. In an exemplary embodiment, control processor 424 causes such resumed full reverse link signal transmissions to continue for at least a predetermined minimum transmitter restoration period, for example.

In an exemplary embodiment, control processor 424 completely gates reverse link transmissions by directing each of the gain blocks 402 to apply approximately zero gain to their respective input signals. Alternatively, control processor 424 may instead cause amplifier 418 to stop transmitting or to transmit at approximately zero power. As described above, after having gated the reverse link signal, the access terminal may resume transmitting a pilot signal before resuming transmissions of other reverse link signal components.

Control processor 424 causes pilot transmissions to resume first by setting the gains in gain blocks 402b, 402c, and 402d to approximately zero while setting the gain in pilot gain block 402a to a non-zero value. In an alternate embodiment, pilot gain block 402a is omitted such that only non-pilot signals are gated or reduced.

In an alternate embodiment, according to one of the algorithms described above, control processor 424 gates or reduces the gains of only a subset of the reverse link signal components. In an exemplary embodiment, only non-pilot signals are gated or transmitted at reduced power using gain blocks 402b, 402c, and 402d to attenuate those signals.

In an exemplary embodiment, control processor 424 also executes a reverse link power control algorithm based on reverse link power control commands received from one or more modem pool transceivers. According to this algorithm, control processor 424 regulates reverse link power using either gain blocks 402 or amplifier 418 or both to change reverse link power. In an exemplary embodiment, control processor 424 either ignores or performs special processing on any reverse link power control commands associated with periods during which the access terminal was not transmitting a full reverse link signal.

One skilled in the art will recognize that the gain-controlled channel signals may be combined differently prior to PN spreader 410 without departing from the described embodiment. For example, summer 408a may add the gain-controlled outputs of gain blocks 402a and 402c instead of 402a and 402b. Alternatively, some signals might be separately gain-controlled and added to both real and imaginary components output by summers 408a and 408b.

In an exemplary embodiment, PN spreader 410 complex-multiplies the outputs of summers 408a and 408b by a complex PN code having components PN_I and PN_Q according to the equations:

$$\begin{aligned} I &= I' PN_I - Q' PN_Q \\ Q &= I' PN_Q + Q' PN_I \end{aligned}$$

In an alternate embodiment, PN spreader 410 multiplies the outputs of summers 408a and 408b by a single real PN sequence according to the equations:

$$\begin{aligned} I &= I' PN \\ Q &= Q' PN \end{aligned}$$

In other embodiments, some other complex or real multiplication equations are used.

In an exemplary embodiment, control processor 424 is a microprocessor, microcontroller, DSP or similar device capable of executing a series of software instructions stored in an electronic medium. In an exemplary embodiment, control processor 424 executes code stored in a memory, for example, memory 422. Control processor 424 may also store temporary values such as access metrics, access metric thresholds, and associated variables in memory 422. In addition, control processor 424 may store temporary values such as reverse power control parameters and timer values associated with maximum transmitter shut-off timer or minimum transmitter restoration timers.

In the embodiments described above, each access terminal sends a reverse link signal to one or more modem pool transceivers. Each modem pool transceiver uses these signals to determine which access terminals will receive forward link transmissions during each forward link time slot. A modem pool transceiver also uses these reverse link signals to determine the greatest data rates at which forward link data may be sent to any access terminal. The reverse link signals may contain DRC information or C/I information, referred to generally as data request information. One skilled in the art will recognize that the data request information may take other forms without departing from the scope of the present invention. For example, an access terminal may transmit symbol error rates or a Yamamoto metric of received forward link signals as data request information.

In an exemplary embodiment, each modem pool transceiver in the access network directs forward link transmissions to one access terminal at a time using a data rate dictated by data request information received from destination access terminal. In such an embodiment, the access terminal demodulates the forward link at a data rate based solely on previously transmitted data request information. Alternatively, the access network may transmit forward link data at a rate other than the rate dictated by the data request information received from destination access terminal. For example, each modem pool transceiver may transmit forward link data to more than one access terminal at data rates chosen by the access network. The destination access terminals determine the rate at which to demodulate the forward link signals by performing blind rate detection or by decoding separate rate indicator signals received from the access network.

The components in the described apparatus embodiments are described in general terms to illustrate the flexibility of the present invention. Each

described component may be implemented using one or a combination of general-purpose microprocessors, digital signal processors (DSP), programmable logic devices, application specific integrated circuits (ASIC), or any other device capable of performing the functions described herein. Though
5 described in terms of a wireless communication system, the embodiments and ideas described herein may also be utilized in a network in which network nodes communicate using other technologies, for example fiber optics, coaxial cable or other wire-line technology.

Thus, the present invention is not intended to be limited to the
10 embodiments shown herein but is to be accorded the widest scope consistent with the principles and novel features disclosed herein.

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205

WHAT IS CLAIMED IS:

1. A method of receiving data transmitted from an access network to an
2 access terminal, the method comprising:
 measuring at the access terminal at least one parameter of a signal
4 received from the access network;
 determining an access metric value based on said measuring;
6 generating data request information based on said measuring;
 comparing the access metric value to an access metric threshold;
8 estimating, based on said comparing, that communicating the data
request information to the access network will not result in selection of the
10 access terminal by the access network; and
 reducing the power of a reverse link signal transmitted from the access
12 terminal to the access network based on said estimating.
2. The method of claim 1 further comprising updating the access metric
2 threshold based on said value of an access metric.
3. The method of claim 1 wherein said measuring further comprises low-
2 pass filtering a forward link data throughput value.
4. The method of claim 3 wherein said low-pass filtering is performed
2 using a finite impulse response filter.
5. The method of claim 3 wherein said low-pass filtering is performed
2 using an infinite impulse response filter.
6. The method of claim 3 wherein said forward link data throughput value
2 is based on a data rate requested by the access terminal.
7. The method of claim 3 wherein said forward link data throughput value
2 is based on a data rate granted by the access network.
8. The method of claim 3 further comprising updating the access metric
2 threshold based on the forward link data throughput value.
9. The method of claim 1 further comprising:
2 receiving an access metric parameter from the access network; and

updating the access metric threshold based on the access metric
4 parameter.

10. The method of claim 9 wherein the access metric parameter is a number
2 of access terminals receiving forward link data from a modem pool transceiver.

11. The method of claim 9 wherein the access metric parameter is an access
2 network metric value associated with a previous forward link data
transmission.

12. The method of claim 1 further comprising:
2 receiving a power control command from the access network at a
receiving time;
4 comparing the receiving time with the time of said reducing; and
processing the power control command in accordance with said
6 comparing.

13. The method of claim 1 wherein said data request information comprises
2 a data rate control value.

14. The method of claim 1 wherein said data request information comprises
2 a carrier-to-interference ratio.

15. The method of claim 1 wherein said reducing further comprises gating a
2 data request information signal based on said estimating, wherein the reverse
link signal comprises a plurality of signal components, and wherein the data
4 request information signal is one of the plurality of signal components.

16. The method of claim 15 wherein said reducing further comprises gating
2 an additional signal component of the plurality of signal components at the
same time as said gating a data request information signal.

17. The method of claim 1 wherein the reverse link signal comprises a
2 plurality of signal components, wherein the plurality signal components
comprises a pilot signal, and wherein said reducing further comprises gating all
4 of said plurality of signal components at the same time as said gating the data
request information signal.

18. The method of claim 17 further comprising:
2 resuming transmission of said pilot signal; and
resuming transmission of at least one other of said plurality of signal
4 components a predetermined period after said resuming transmission of said
pilot signal.

19. The method of claim 1 further comprising:
2 monitoring the length of time during which the power of the reverse link
signal is reduced in accordance with said reducing; and
4 discontinuing said reducing when the length of time exceeds a
predetermined maximum transmitter shut-off period.

20. The method of claim 1 further comprising multiplying the reverse link
2 signal by a PN code.

21. The method of claim 1 further comprising complex-multiplying the
2 reverse link signal by a complex PN code.

22. An access terminal apparatus comprising:
2 a data request gain module configured to gain-control a data request
information signal, based on a data request gain control signal, to produce a
4 gain-controlled data request information signal; and
a control processor configured to generate an estimate of whether
6 transmitting the data request information signal would result in selection of the
access terminal by the access network, and to alter the gain control signal based
8 on the estimate.

a control processor configured to determine an access metric value based
10 on measurements of at least one parameter of a signal received from the access
network, generate data request information based on the measurements,
12 compare the access metric value to an access metric threshold, estimate that
communicating the data request information to the access network will not
14 result in selection of the access terminal by the access network, and to alter the
gain control signal based on the estimate.

23. The apparatus of claim 22 further comprising a Walsh spreader
2 configured to spread the data request information signal using a Walsh code.

24. The apparatus of claim 22 wherein the control processor is further
2 configured to determine an average throughput value, and to generate the
estimate based on the average throughput value.

25. The apparatus of claim 22 wherein the control processor is further
2 configured to determine an access metric value and an access metric threshold
value, and to generate the estimate based on comparing the access metric value
4 to the access metric threshold.

26. The apparatus of claim 25 wherein the control processor is further
2 configured to update the average throughput value based on at least one access
metric parameter received from an access network.

27. The apparatus of claim 25 wherein the control processor is further
2 configured to update the average throughput value based on a number
received from an access network, wherein the number corresponds to a number
4 of access terminals receiving forward link data from a modem pool transceiver.

28. The apparatus of claim 25 wherein the control processor is further
2 configured to update the average throughput value based on an access network
access metric value received from an access network.

29. The apparatus of claim 22 further comprising a pilot gain module
2 configured gain-control a pilot signal component based on a pilot gain control
signal to produce a gain-controlled pilot signal, wherein the control processor is
4 further configured to alter the pilot gain control to gate the pilot signal based on
the estimate.

30. The apparatus of claim 29 wherein the control processor is further
2 configured to alter the pilot gain control to increase the gain of the pilot signal
at a first time, and to alter the data request gain control signal to increase the
4 gain of the data request information signal at a second time, wherein the second
time is a predetermined duration later than the first time.

31. The apparatus of claim 22 further comprising a PN spreader configured
2 to multiply the data request information signal by a PN code.

32. The apparatus of claim 22 further comprising a complex PN spreader
2 configured to complex-multiply the data request information signal by a
complex PN code.

33. An access terminal apparatus comprising:
2 an amplifier configured to gate an upconverted signal based on a gating
control signal; and
4 a control processor configured to generate an estimate of whether
transmitting a data request information signal would result in selection of the
6 access terminal by the access network, and to alter the gating control signal
based on the estimate.

34. The apparatus of claim 33 wherein the control processor is further
2 configured to determine an average throughput value, and to generate the
estimate based on the average throughput value.

35. The apparatus of claim 33 wherein the control processor is further
2 configured to determine an access metric value and an access metric threshold
value, and to generate the estimate based on comparing the access metric value
4 to the access metric threshold.

36. The apparatus of claim 35 wherein the control processor is further
2 configured to update the average throughput value based on at least one access
metric parameter received from an access network.

37. The apparatus of claim 35 wherein the control processor is further
2 configured to update the average throughput value based on a number
received from an access network, wherein the number corresponds to a number
4 of access terminals receiving forward link data from a modem pool transceiver.

38. The apparatus of claim 35 wherein the control processor is further
2 configured to update the average throughput value based on an access network
access metric value received from an access network.

39. The apparatus of claim 33 further comprising a PN spreader configured
2 to multiply the data request information signal by a PN code.

2

2

6

ABSTRACT

In a high data rate communication system, a method and apparatus for
5 selectively reducing the power of signals transmitted by an access terminal.
The access terminal generates an access metric based on throughput or data rate
control (DRC) information. The access terminal then compares the access
metric to an access metric threshold and gates or reduces its transmit power
based on the results of the comparison. The access terminal uses algorithms to
10 determine the access metric and access metric threshold that reduce transmit
power during periods when the access terminal would not be selected to
receive data from an access network according to an access network selection
algorithm.



FIG. 2a






FIG. 26




FIG. 3





FIG. 4



COMBINED DECLARATION / POWER OF ATTORNEY

ATTORNEY DOCKET NO.: PA000469

AS BELOW NAMED INVENTOR, I HEREBY DECLARE THAT: This Declaration is of the following type:

☒ Original ☐ Supplemental ☐ Continuation-In-Part ☐ Divisional
☐ Continuation ☐ National Stage of PCT

My residence, post office address and citizenship are as stated below next to my name: I believe I am the original, first and sole inventor (if only one name is listed below) or an original, first and joint inventor (if plural names are listed below) of the subject matter which is claimed and for which a patent is sought on the invention **METHOD AND APPARATUS FOR REDUCING TRANSMISSION POWER IN A HIGH DATA RATE SYSTEM** the specification of which:

☒ is attached hereto.
☐ was filed on _____ as Serial No. _____
☐ was amended on _____ (if applicable).
☐ was described and claimed in PCT International Application No. _____ filed on _____ and as amended under PCT Article 19 on _____

I hereby state that I have reviewed and understand the contents of the above-identified specification, including the claims, as amended by any amendment referred to above. I acknowledge the duty to disclose information which is material to the examination of this application in accordance with Title 37, Code of Federal Regulations, Sec. 1.56(a).

I hereby claim foreign priority benefits under Title 35, United States Code, Sec. 119 of any foreign application(s) for patent or inventor's certificate or of any PCT International application(s) designating at least one country other than the United States of America listed below and have also identified below any foreign application(s) for patent or inventor's certificate or any PCT International application(s) designating at least one country other than the United States of America filed by me on the same subject matter having a filing date before that of the application(s) of which priority is claimed.

Priority Claimed

(Country)

(Application No.)

(Day/Month/Year/Filed)

(Yes)

(No)

I hereby claim the benefit under Title 35 USC 120 of the United States application(s) listed below, and insofar as the subject matter of each of the claims of this application is not disclosed in the prior United States application in the manner provided by the first paragraph of Title 35 USC 112, I acknowledge the duty to disclose material information as defined in Title 37 CFR 1.56(a) which occurred between the filing date of the prior application and the national or PCT International filing date of this application:

(Serial No.)

(Filing Date)

(Status)

I hereby appoint the following attorneys and/or agents to prosecute this application and to transact all business in the U.S. Patent and Trademark Office connected therewith: Russell B. Miller, Reg. No. 31,122, Gregory D. Ogrod, Reg. No. 30,880, Bruce W. Greenhaus, Reg. No. 37,339, Charles D. Brown, Reg. No. 28,285, Thomas R. Rouse, Reg. No. 40,793, Kent D. Baker, Reg. No. 38,822, Thomas M. Thibault, Reg. No. 42,181, Tom Streeter, Reg. No. 32,007, Christopher O. Edwards, Reg. No. 36,127, Pavel Kalousek, Reg. No. 44,178, Kyong H. Macek, Reg. No. 42,977, Byron Yafuso, Reg. No. 45,244, Raymond B. Hom, Reg. No. 44,773, Kevin J. Clark, Reg. No. 42,421, Sean English, Reg. No. 37,319, Roger W. Martin, Reg. No. 39,291, Sandip S. Minhas, Reg. No. 44,945, Michael D. Hartogs, Reg. No. 36,547, Philip R. Wadsworth, Reg. No. 29,219, S. Hossain Beladi, Reg. No. 42,311, Albert J. Harnois, Reg. No. 46,123, Sandra L. Godsey, Reg. No. 42,589, and Maryanne E. DeAngelo, Reg. No. P47,288. Please direct all telephone calls to Philip R. Wadsworth at (858) 651-4404 and address all correspondence to: Sarah Kirkpatrick, Manager, Intellectual Property Administration, QUALCOMM Incorporated, 5775 Morehouse Drive, San Diego, California 92121-1714.

I hereby declare that all statements made herein of my own knowledge are true and that all statements made on information and belief are believed to be true; and further that these statements were made with the knowledge that willful false statements and the like so made are punishable by fine or imprisonment, or both, under Section 1001 of Title 18 of the United States Code and that such willful false statements may jeopardize the validity of the application or any patent issued thereon.

Full Name of First or Joint Inventor Stein A. Lundby	Inventor Signature	Date
Residence 716 North Granados Avenue, Solana Beach, California 92075	Citizenship Switzerland	
Post Office Address 716 North Granados Avenue, Solana Beach, California 92075		